LA-UR-13-26853

Approved for public release; distribution is unlimited.

Title: Analytical and Numerical Analysis of Free-Electron Lasers - Lecture 3

Author(s): Freund, Henry P.

Intended for: Seminae Class at the Univ. of New Mexico at Albuquerque

Issued: 2013-09-03

Disclaimer:

Los Alamos National Laboratory, an affirmative action/equal opportunity employer, is operated by the Los Alamos National Security, LLC for the National Nuclear Security Administration of the U.S. Department of Energy under contract DE-AC52-06NA25396. By approving this article, the publisher recognizes that the U.S. Government retains nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or to allow others to do so, for U.S. Government purposes. Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy. Los Alamos National Laboratory strongly supports academic freedom and a researcher's right to publish; as an institution, however, the Laboratory does not endorse the viewpoint of a publication or guarantee its technical correctness.

THEORETICAL AND NUMERICAL ANALYSIS OF FREE-ELECTRON LASERS

LECTURE 3

LINEAR THEORY OF STIMULATED EMISSION IN ONE-DIMENSION FOR HELICAL WIGGLER FIELDS

OUTLINE

- The intent of this lecture is to discuss the gain in the linear regime in 1-D
 - Planar & helical wigglers
 - Low-Gain Regime
 - Gain Formula
 - Efficiency Estimate
 - High-Gain Regime
 - Recovery of the Low-Gain Regime
 - Compton & Raman Regimes
 - Efficiency Estimates
 - Thermal Effects

THE PLASMA FREQUENCY

- We have used a normalized plasma frequency

$$\omega_b^2 = \frac{4\pi e^2 n_b}{m_e}$$

- This depends on the current density

$$\begin{array}{ccc} J = en_b c & & \\ J = \frac{I_b}{\pi R_b^2} & \xrightarrow{\text{red arrow}} & \frac{I_b}{\pi R_b^2} = en_b c \end{array}$$

- We can relate the normalized plasma frequency to the current density as follows

$$\frac{\omega_b^2}{c^2 k_w^2} = \frac{4e}{m_e c^3} \frac{I_b}{k_w^2 R_b^2} = \frac{4}{k_w^2 R_b^2} \frac{I_b}{I_A}$$

where

$$\frac{m_e c^3}{e} = I_A \approx 17,000 \text{ A}$$

LOW-GAIN LIMIT: HELICAL WIGGLER

- Due to the helical symmetry, the analysis of the linear gain is simpler for a helical wiggler
- The idealized 1-D model of a helical wiggler is

$$\mathbf{B}_w(z) = B_w(\hat{\mathbf{e}}_x \cos k_w z + \hat{\mathbf{e}}_y \sin k_w z)$$

- Using a slowly-varying amplitude and phase approximation, an electron propagating through the helical wiggler interacts with a circularly polarized wave

$$\delta \mathbf{A}(z, t) = \delta A(z) [\hat{\mathbf{e}}_x \cos(kz - \omega t + \delta\varphi(z)) - \hat{\mathbf{e}}_y \sin(kz - \omega t + \delta\varphi(z))]$$

- The slowly-varying envelope approximation (SVEA) requires that

$$\frac{1}{\delta A} \frac{\partial}{\partial z} \delta A \ll k \quad \frac{1}{\delta\varphi} \frac{\partial}{\partial z} \delta\varphi \ll k$$

MAXWELL'S EQUATION

- In 1-D, Maxwell's equation for the vector potential is

$$\left(\frac{\partial^2}{\partial z^2} - \frac{1}{c^2} \frac{\partial^2}{\partial t^2} \right) \delta \mathbf{A}(z,t) = - \frac{4\pi}{c} \delta \mathbf{J}_\perp(z,t)$$

- Taking the appropriate derivatives yields

$$\frac{\partial^2}{\partial t^2} \delta \mathbf{A}(z,t) = - \omega^2 \delta \mathbf{A}(z,t)$$

$$\begin{aligned} \frac{\partial^2}{\partial z^2} \delta \mathbf{A}(z,t) = & - \left[\frac{d^2}{dz^2} - (k + \delta\varphi')^2 \right] \delta \mathbf{A}(z,t) \\ & - 2(k + \delta\varphi')^{1/2} \frac{d}{dz} \left[(k + \delta\varphi')^{1/2} \delta A \right] \left[\hat{\mathbf{e}}_x \sin(kz - \omega t + \delta\varphi) \right. \\ & \left. + \hat{\mathbf{e}}_y \cos(kz - \omega t + \delta\varphi) \right] \end{aligned}$$

 $\delta\varphi' = \frac{\partial}{\partial z} \delta\varphi = \delta k$

- These derivatives can be inserted into Maxwell's equations to obtain the evolution equations for the amplitude and phase

MAXWELL'S EQUATIONS - 2

- The helical wiggler field is derivable from a vector potential of the form

$$\left(\frac{d^2}{dz^2} + \frac{\omega^2}{c^2} - (k + \delta\varphi')^2 \right) \delta A \cos(kz - \omega t + \delta\varphi) - 2(k + \delta\varphi')^{1/2} \frac{d}{dz} \left[(k + \delta\varphi')^{1/2} \delta A \right] \sin(kz - \omega t + \delta\varphi) = -\frac{4\pi}{c} \delta J_x$$

2nd order term in the derivative can be neglected

$$\left(\frac{d^2}{dz^2} + \frac{\omega^2}{c^2} - (k + \delta\varphi')^2 \right) \delta A \sin(kz - \omega t + \delta\varphi) + 2(k + \delta\varphi')^{1/2} \frac{d}{dz} \left[(k + \delta\varphi')^{1/2} \delta A \right] \cos(kz - \omega t + \delta\varphi) = \frac{4\pi}{c} \delta J_y$$

2nd order derivative in $\delta\varphi$ means that this term can be extracted from the derivative

1st ORDER MAXWELL'S EQUATIONS

- Neglecting the 2nd order derivatives of the amplitude and phase yields the following equations

$$\left(\frac{\omega^2}{c^2} - (k + \delta k)^2\right)\delta A \cos(kz - \omega t + \delta\varphi) - 2(k + \delta k)\frac{d}{dz}\delta A \sin(kz - \omega t + \delta\varphi) = -\frac{4\pi}{c}\delta J_x$$

$$\left(\frac{\omega^2}{c^2} - (k + \delta k)^2\right)\delta A \sin(kz - \omega t + \delta\varphi) + 2(k + \delta k)\frac{d}{dz}\delta A \cos(kz - \omega t + \delta\varphi) = \frac{4\pi}{c}\delta J_y$$

- Multiplying the 1st [2nd] equation by $\sin(kz - \omega t + \delta\varphi)$ [$\cos(kz - \omega t + \delta\varphi)$] and subtracting the 2nd equation from the 1st yields an equation for the amplitude

$$2(k + \delta k)\frac{d}{dz}\delta A = \frac{4\pi}{c}(\delta J_x \sin(kz - \omega t + \delta\varphi) + \delta J_y \cos(kz - \omega t + \delta\varphi))$$

 $\approx 2k\frac{d}{dz}\delta A$

- Multiplying the 1st [2nd] equation by $\sin(kz - \omega t + \delta\varphi)$ [$\cos(kz - \omega t + \delta\varphi)$] and subtracting the 2nd equation from the 1st yields an equation for the amplitude

$$\left(\frac{\omega^2}{c^2} - (k + \delta k)^2\right)\delta A = -\frac{4\pi}{c}(\delta J_x \cos(kz - \omega t + \delta\varphi) - \delta J_y \sin(kz - \omega t + \delta\varphi))$$

 $\approx -2\frac{\omega}{c^2}\delta k\delta A$

THE GAIN EQUATION

- We transform to the frame rotating with the wiggler where

$$v_x = v_1 \cos k_w z - v_2 \sin k_w z \quad v_y = v_1 \sin k_w z + v_2 \cos k_w z$$

- In this frame, the gain equation becomes

$$2k \frac{d}{dz} \delta A = \frac{4\pi}{c} [\delta J_1 \sin \psi - \delta J_2 \cos \psi]$$

$v_2 = 0$ for the lowest order orbits

$$\frac{d}{dz} \delta A = \frac{2\pi}{\omega} \delta J_1 \sin \psi$$

- The phase equation is a *simple* algebraic (not differential) equation

$$\delta k = \frac{2\pi}{\omega \delta A} \delta J_1 \cos \psi$$

- In the low-gain regime we assume that the current density is low enough that we can neglect the effect on the wavenumber so that $k = \omega/c$
- This is not the case when we formulate the equations for nonlinear simulations which employ similar equations for the field

THE SOURCE CURRENT

- For a monoenergetic, DC beam with a uniform phase distribution, we can write the source current as

$$\begin{aligned}\delta J_1(z, t) &= -en_b v_{z0} \int_{-\infty}^{\infty} dt_0 v_1(z, t_0) \delta[z - z(t, t_0)] \\ &= -en_b v_{z0} \int_{-\infty}^{\infty} dt_0 v_1(t, t_0) \frac{\delta[t - \tau(z, t_0)]}{|v_z(z, t_0)|}\end{aligned}$$

- The Lagrangian time coordinate is

$$\tau(z, t_0) = t_0 + \int_0^z \frac{dz'}{v_z(z', t_0)} \longrightarrow \text{This is the axial velocity of an electron at } z' \text{ that entered the wiggler at time } t_0$$

- Using this current, and averaging the gain equation over a wave period, we find that

$$2k \frac{d}{dz} \delta a = - \frac{\omega_b^2}{c^2} \beta_{z0} \frac{\omega}{2\pi} \int_0^{2\pi/\omega} dt \int_{-\infty}^{\infty} dt_0 v_1 \sin \psi \frac{\delta[t - \tau(z, t_0)]}{|v_z(z, t_0)|}$$

where $\delta a = e\delta A/m_e c^2$ is a normalized (dimensionless) field amplitude

THE QUASI-STATIC ASSUMPTION

- **Quasi-Static Assumption:** particles entering the interaction region at intervals of the wave period execute the same trajectories

$$\rightarrow \mathbf{v}(t + 2\pi N/\omega, t_0 + 2\pi N/\omega) = \mathbf{v}(t, t_0)$$

- If we average Maxwell's equations over a wave period, then we get integrals of the form

$$\int_0^{2\pi/\omega} dt \int_{-T}^T dt_0 G(z, t, t_0) \delta[t - \tau(z, t_0)] = \int_0^{2\pi/\omega} dt_0 G[z, \tau(z, t_0), t_0]$$

- This is essentially a DC beam approximation, which was certainly valid for treating low energy microwave tubes (*i.e.*, TWTs), but it works well for FELs when the bunch length is greater than the slippage length
- Under the quasi-static assumption, the gain equation becomes

$$2k \frac{d}{dz} \delta a = - \frac{\omega_b^2}{c^2} \beta_{z0} \frac{\omega}{2\pi} \int_0^{2\pi/\omega} dt_0 \frac{v_1 \sin \psi}{|v_z|} = - \frac{\omega_b^2}{c^2} \frac{v_w}{c} \langle \sin \psi \rangle$$

where

$$\langle \sin \psi \rangle = \frac{1}{2\pi} \int_0^{2\pi} d\psi_0 \sin \psi(\psi_0)$$

UNTRAPPED TRAJECTORIES

- In the absence of a tapered wiggler, the ponderomotive phase satisfies the nonlinear pendulum equation

$$\frac{d^2 \psi}{dz^2} = -\mu^2 \sin \psi \qquad \mu^2 = \frac{(k + k_w)^2}{\beta_{\parallel}^2 \gamma^2 \gamma_{\parallel}^2} K \delta a$$

- We look for perturbative solutions where

$$\psi \approx \psi_0 + \left(k + k_w - \frac{\omega}{v_{\parallel}} \right) z + \delta \psi$$

 $\Delta k = k + k_w - \frac{\omega}{v_{\parallel}}$

- The perturbed ponderomotive phase satisfies

$$\frac{d^2}{dz^2} \delta \psi \approx -\mu^2 \sin(\psi_0 + \Delta k z)$$

which has the solution

$$\delta \psi = \frac{\mu^2}{\Delta k^2} [\sin(\psi_0 + \Delta k z) - \sin \psi_0 - \Delta k z \cos \psi_0]$$

THE PHASE AVERAGE

- The phase average becomes

$$\begin{aligned}
 \langle \sin \psi \rangle &\approx \langle \sin (\psi_0 + \Delta k z) \rangle + \frac{\mu^2}{\Delta k^2} \langle \sin \psi_0 \cos \psi_0 \rangle (\cos^2 \Delta k z - \sin^2 \Delta k z) \\
 &+ \frac{\mu^2}{\Delta k^2} \sin \Delta k z \cos \Delta k z \langle \cos^2 \psi_0 - \sin^2 \psi_0 \rangle + \frac{\mu^2}{\Delta k^2} \cos \Delta k z \langle \sin \psi_0 \cos \psi_0 \rangle \\
 &+ \frac{\mu^2}{\Delta k^2} \sin \Delta k z \langle \sin^2 \psi_0 \rangle - \frac{\mu^2}{\Delta k^2} \Delta k z \cos \Delta k z \langle \cos^2 \psi_0 \rangle \\
 &+ \frac{\mu^2}{\Delta k^2} \Delta k z \sin \Delta k z \langle \sin \psi_0 \cos \psi_0 \rangle
 \end{aligned}$$

- The only terms that survive are those in $\langle \sin^2 \psi \rangle = \langle \cos^2 \psi \rangle = 1/2$, so that

$$\langle \sin \psi \rangle \approx \frac{\mu^2}{2\Delta k^2} (\sin \Delta k z - \Delta k z \cos \Delta k z)$$

THE GAIN

- The gain is given by

$$G(L) = \frac{1}{\delta a} \int_0^L dz \frac{d}{dz} \delta a = - \frac{\omega_b^2}{2\omega c} \frac{K}{\gamma \delta a} \int_0^L dz \langle \sin \psi \rangle$$

$$= \frac{\omega_b^2}{4c^2} \frac{K^2}{\gamma^2} \frac{(k + k_w)^2}{\omega \beta_{\parallel} \gamma \gamma_{\parallel}^2} \frac{1}{\Delta k^2} \int_0^L dz (\sin \Delta k z - \Delta k z \cos \Delta k z)$$

- Integration over z yields ($\Theta = \Delta k L/2$)

$$\frac{1}{\Delta k^2} \int_0^L dz (\sin \Delta k z - \Delta k z \cos \Delta k z) = - \frac{L^3}{4} \frac{d}{d\Theta} \left(\frac{\sin \Theta}{\Theta} \right)^2$$

- So that the gain can be expressed as

$$G(L) = \frac{\omega_b^2 L^3 k}{8 \gamma \gamma_{\parallel}^2 c^2} \frac{K^2}{\gamma^2} \frac{d}{d\Theta} \left(\frac{\sin \Theta}{\Theta} \right)^2 \approx \frac{\pi}{2} \frac{\omega_b^2}{\gamma c^2 k_w^2} N_w^3 \frac{K^2}{\gamma^2} \frac{d}{d\Theta} \left(\frac{\sin \Theta}{\Theta} \right)^2$$

PROPERTIES OF THE GAIN

- The gain is proportional to the derivative with respect to Θ of the spontaneous emission
 - Often referred to as Madey's Theorem
- The spectral function reaches extrema of about ∓ 0.54 at $\Theta = \pm 1.3$
 - The frequency at which peak gain occurs ($\Theta = -1.3$) is

$$\omega = \frac{k_w v_{\parallel}}{1 - \beta_{\parallel}} \left(1 - \frac{2.6}{k_w L} \right) \approx \frac{2\gamma^2 k_w c}{1 + K^2} \left(1 - \frac{2.6}{k_w L} \right)$$

- The frequency spread is comparable to that for spontaneous emission

$$\frac{\Delta\omega}{\omega} \approx \frac{\lambda_w}{L}$$

- Since $\Delta\omega/\omega \approx 2\gamma_{\parallel}^2 \Delta v_{\parallel}/v_{\parallel}$, the cold beam approximation is valid when

$$\frac{\Delta v_{\parallel}}{v_{\parallel}} \ll \frac{\lambda}{L}$$

THE SATURATION EFFICIENCY

- The kinetic energy of an electron is

$$T = (\gamma - 1)m_e c^2$$

- The efficiency is the ratio of the kinetic energy loss to the initial kinetic energy

$$\eta = \frac{\Delta T}{(\gamma - 1)m_e c^2} = \frac{1}{(\gamma - 1)} \frac{d\gamma}{dv_{\parallel}} \Delta v_{\parallel}$$

- The derivative of γ with respect to the axial velocity is

$$\gamma^2 = 1 + \gamma^2 \frac{v_{\parallel}^2}{c^2} + \frac{p_{\perp}^2}{m_e^2 c^2} \rightarrow \gamma^2 = \gamma_{\parallel}^2 \left(1 + \frac{p_{\perp}^2}{m_e^2 c^2} \right) \rightarrow \frac{d\gamma}{dv_{\parallel}} = \gamma \gamma_{\parallel}^2 \frac{v_{\parallel}}{c^2}$$

- The change in the axial velocity at saturation is twice the difference in velocity between the beam and the ponderomotive wave [Slater, *Microwave Electronics*, 1950]

$$\Delta v_{\parallel} = -2(v_{\parallel} - v_{ph})$$

As a result

$$\eta = \frac{\gamma}{\gamma - 1} \frac{\beta_{\parallel}}{(1 - \beta_{\parallel})} (\beta_{\parallel} - \beta_{ph}) \approx \frac{2\gamma \gamma_{\parallel}^2 v_{\parallel} (v_{\parallel} - v_{ph})}{\gamma - 1 c^2}$$

THE LOW GAIN EFFICIENCY

- Using the phase velocity corresponding to the peak gain

$$\begin{aligned}
 \frac{\Delta v_{\parallel}}{c} &= \beta_{\parallel} - \beta_{ph} = \beta_{\parallel} - \frac{\omega_{res}(1 - 2.6/k_w L)}{\omega_{res}(1 - 2.6/k_w L) + k_w c} \\
 &\approx \frac{1}{\omega_{res}} [\beta_{\parallel} \omega_{res}(1 - 2.6/k_w L) + k_w v_{\parallel} - \omega_{res}(1 - 2.6/k_w L)] \\
 &= \frac{1}{\omega_{res}} [k_w v_{\parallel} - (1 - \beta_{\parallel}) \omega_{res}(1 - 2.6/k_w L)] \\
 &= \frac{1}{\omega_{res}} [k_w v_{\parallel} - k_w v_{\parallel}(1 - 2.6/k_w L)] \\
 &= (1 - \beta_{\parallel}) \frac{2.6}{k_w L} \approx (1 - \beta_{\parallel}) \frac{1}{2.4 N_w} \approx \frac{\gamma_{\parallel}^2}{2} \frac{1}{2.4 N_w}
 \end{aligned}$$

- As a result, in the relativistic regime where $\beta_{\parallel} \approx 1$ and $\gamma \gg 1$, we have

$$\eta \approx \frac{1}{2.4 N_w} \xrightarrow{\text{often simplified to}} \eta \approx \frac{1}{2 N_w}$$

LOW GAIN: PLANAR WIGGLER

- The low gain result for a planar wiggler differs from that for a helical wiggler in that
 - K is replaced by K_{rms}
 - Harmonic interactions arise due to the oscillatory velocity
 - The JJ factor describes the coupling between different harmonic contributions
- The gain can be written as

$$G(L) = \frac{\omega_b^2 L^3 k}{8\gamma\gamma_{||}^2 c^2} \frac{K_{rms}^2}{\gamma^2} JJ_m(b) \frac{d}{d\Theta_{2m+1}} \left(\frac{\sin \Theta_{2m+1}}{\Theta_{2m+1}} \right)^2$$

where $m = 0$ describes the fundamental, $m = 1$ describes the 3rd harmonic, *etc.* and

$$\Theta_m = \frac{L}{2} \left(\frac{\omega}{v_{||}} - k - mk_w \right)$$

$$JJ_m(b) = [J_m(b) - J_{m+1}(b)]^2$$

$$b = \frac{1 + 2m}{2} \frac{K_{rms}^2}{(1 + K_{rms}^2)}$$

THE HIGH-GAIN REGIME

- The high-gain regime exhibits two basic limiting cases
 - Compton Regime: ponderomotive potential is dominant over the space-charge potential
 - Relevant to all modern high-gain FELs
 - Raman Regime: space-charge potential is dominant over the ponderomotive potential
 - Relevant to early microwave FELs
- We describe a Vlasov-Maxwell analysis of the dispersion equation for a helical wiggler in one-dimension
 - Since the orbit equations are independent of x and y , the canonical momenta in these dimensions are constants of the motion
 - The energy is also a constant of the motion
 - The distribution function can be written in general terms as functions of these constants of the motion

$$F_b(P_x, P_y, p) = n_b G_{\perp}(P_x, P_y) G_b(p)$$

- We now solve for the perturbed distribution function

THE GENERAL PROCEDURE

- Solving for the perturbed distribution by the method of characteristics where we integrate over the unperturbed trajectories gives

$$\delta f_b[z, \mathbf{p}, \tau(z)] = e \int_0^z \frac{dz'}{v_z(z')} \left\{ \delta \mathbf{E}[z, \tau(z)] + \frac{1}{c} \mathbf{v}(z') \times \delta \mathbf{B}[z, \tau(z)] \right\} \cdot \nabla_{\mathbf{p}} F_b$$

- Using the perturbed distribution, we solve Maxwell's equations

$$\left(\frac{\partial^2}{\partial z^2} - \frac{1}{c^2} \frac{\partial^2}{\partial t^2} \right) \delta \mathbf{A}_{\perp} = - \frac{4\pi}{c} \delta \mathbf{J}_{\perp}(z, t) \longrightarrow \text{wave equation}$$

$$\frac{\partial^2}{\partial z \partial t} \delta \varphi = 4\pi \delta J_z(z, t) \longrightarrow \text{z-component of Ampere's Law}$$

not easy to include in 3-D

- The source current can be expressed in terms of the perturbed distribution as

$$\delta \mathbf{J}(z, t) = - \frac{e}{m_e} \int d^3 p \frac{1}{\gamma} \mathbf{p} \delta f_b(z, \mathbf{p}, t)$$

THE IDEALIZED DISTRIBUTION

- An idealized electron beam is both mono-energetic and has a vanishing pitch-angle spread. The pitch-angle spread is described by non-vanishing canonical momenta.
- We first impose the condition of a vanishing pitch-angle spread where $P_x = P_y = 0$ as follows

$$F_b(P_x, P_y, p) = n_b \delta(P_x) \delta(P_y) G_b(p)$$

- Ultimately, we will also impose a mono-energetic beam assumption as well, where

$$G_b(p) = \delta(p - p_0)$$

where the energy of the beam is given by $\gamma_0 = (1 + p_0^2/m_e^2 c^2)^{1/2}$.

THE CANONICAL COORDINATES

- We transform from $(p_x, p_y, p_z) \rightarrow (P_x, P_y, p)$

$$p_x = P_x \cos \Omega_0 t - P_y \sin \Omega_0 t + p_w \cos k_w z$$

$$p_y = P_x \sin \Omega_0 t + P_y \cos \Omega_0 t + p_w \sin k_w z$$

$$p_z = \sqrt{p^2 - p_x^2 - p_y^2}$$

$$\frac{\partial P_x}{\partial p_x} = \frac{\partial P_y}{\partial p_y} = \cos \Omega_0 t \quad \frac{\partial P_x}{\partial p_y} = -\frac{\partial P_y}{\partial p_x} = \sin \Omega_0 t$$

$$\frac{\partial p}{\partial p_x} = \frac{p_x}{p} \frac{\partial}{\partial p} \quad \frac{\partial p}{\partial p_y} = \frac{p_y}{p} \frac{\partial}{\partial p} \quad \frac{\partial p}{\partial p_z} = \frac{p_z}{p} \frac{\partial}{\partial p}$$

- As a result, the transformation of the derivatives take the form

$$\frac{\partial}{\partial p_x} = \cos \Omega_0 t \frac{\partial}{\partial P_x} - \sin \Omega_0 t \frac{\partial}{\partial P_y} + \frac{p_x}{p} \frac{\partial}{\partial p}$$

$$\frac{\partial}{\partial p_y} = \sin \Omega_0 t \frac{\partial}{\partial P_x} + \cos \Omega_0 t \frac{\partial}{\partial P_y} + \frac{p_y}{p} \frac{\partial}{\partial p}$$

$$\frac{\partial}{\partial p_z} = \frac{p_z}{p} \frac{\partial}{\partial p}$$

THE ROTATING FRAME

- We transform to a circularly polarized rotating frame

$$\hat{\mathbf{e}}_{\pm} = \frac{1}{2} (\hat{\mathbf{e}}_x \pm i\hat{\mathbf{e}}_y)$$

$$\hat{\mathbf{e}}_+ \times \hat{\mathbf{e}}_- = -\frac{i}{2} \hat{\mathbf{e}}_z \quad \hat{\mathbf{e}}_{\pm} \times \hat{\mathbf{e}}_z = \pm i \hat{\mathbf{e}}_{\pm} \quad \hat{\mathbf{e}}_+ \cdot \hat{\mathbf{e}}_+ = \hat{\mathbf{e}}_- \cdot \hat{\mathbf{e}}_- = 0 \quad \hat{\mathbf{e}}_+ \cdot \hat{\mathbf{e}}_- = \frac{1}{2}$$

- In this frame the components of the momentum and the momentum-space gradient can be expressed as

$$p_{\pm} = p_x \mp ip_y = p_w e^{\mp ik_w z} + (P_x \mp iP_y) e^{\mp i\Omega_0 t}$$

$$\nabla_{\mathbf{p}} = \hat{\mathbf{e}}_+ \left(\frac{\partial}{\partial p_x} - i \frac{\partial}{\partial p_y} \right) + \hat{\mathbf{e}}_- \left(\frac{\partial}{\partial p_x} + i \frac{\partial}{\partial p_y} \right) + \hat{\mathbf{e}}_z \frac{\partial}{\partial p_z}$$

- The momentum-space gradient can be expressed in terms of the canonical variables as

$$\frac{\partial}{\partial p_x} \mp i \frac{\partial}{\partial p_y} = e^{\mp i\Omega_0 t} \left(\frac{\partial}{\partial P_x} \mp i \frac{\partial}{\partial P_y} \right) + \frac{P_{\pm}}{P} \frac{\partial}{\partial P}$$

$$\frac{\partial}{\partial p_z} = \frac{P_z}{P} \frac{\partial}{\partial P}$$

THE ROTATING FIELDS

- In transforming the fields to the rotating frame, we note that

$$\delta \mathbf{A}_\perp(z,t) = (\delta \hat{A}_+(z) \hat{\mathbf{e}}_+ + \delta \hat{A}_-(z) \hat{\mathbf{e}}_-) e^{-i\omega t} + c.c.$$

$$\delta \hat{A}_\pm = \frac{1}{2} (\delta \hat{A}_x \mp i \delta \hat{A}_y)$$

$$\delta \varphi(z,t) = \frac{1}{2} \delta \hat{\varphi}(z) e^{-i\omega t} + c.c.$$

$$\delta \mathbf{E}(z,t) = \left[-\frac{1}{2} \frac{\partial}{\partial z} \delta \hat{\varphi} \hat{\mathbf{e}}_z + i \frac{\omega}{c} (\delta \hat{A}_+ \hat{\mathbf{e}}_+ + \delta \hat{A}_- \hat{\mathbf{e}}_-) \right] e^{-i\omega t} + c.c.$$

hence

$$\delta \mathbf{B}(z,t) = -i \frac{\partial}{\partial z} (\delta \hat{A}_+ \hat{\mathbf{e}}_+ - \delta \hat{A}_- \hat{\mathbf{e}}_-) e^{-i\omega t} + c.c.$$

- As a result, the Lorentz force equation becomes

$$\begin{aligned} \delta \mathbf{E} + \frac{1}{c} \mathbf{v} \times \delta \mathbf{B} = & \frac{1}{2} \left[-\frac{\partial}{\partial z} \delta \hat{\varphi} + \frac{1}{\gamma m_e c} \left(p_- \frac{\partial}{\partial z} \delta \hat{A}_+ + p_+ \frac{\partial}{\partial z} \delta \hat{A}_- \right) \right] \hat{\mathbf{e}}_z e^{-i\omega t} \\ & + \frac{1}{c} \left(i\omega - v_z \frac{\partial}{\partial z} \right) (\delta \hat{A}_+ \hat{\mathbf{e}}_+ + \delta \hat{A}_- \hat{\mathbf{e}}_-) e^{-i\omega t} + c.c. \end{aligned}$$

THE PERTURBED DISTRIBUTION

- The 1st order Vlasov equation is expressible in general form as

$$\frac{d}{dt}\delta f_b(z, \mathbf{p}, t) = e \left[\delta \mathbf{E}(z, t) + \frac{1}{c} \mathbf{v} \times \delta \mathbf{B}(z, t) \right] \cdot \nabla_{\mathbf{p}} F_b(P_x, P_y, p)$$

- As a result, the perturbed distribution function becomes

$$\delta f_b(z, \mathbf{p}, \tau(z)) = e \int_0^z \frac{dz'}{v_z(z')} \left[\delta \mathbf{E}(z', t) + \frac{1}{c} \mathbf{v}(z') \times \delta \mathbf{B}(z', t) \right] \cdot \nabla_{\mathbf{p}(z')} F_b$$

- The axial variation of the perturbed distribution is

$$\delta \hat{f}_b(z, \mathbf{p}) = e \int_0^z dz' \frac{e^{i\omega\tau(z, z')}}{v_z(z')} \left[\delta \hat{\mathbf{E}}(z') + \frac{1}{c} \mathbf{v}(z') \times \delta \hat{\mathbf{B}}(z') \right] \cdot \nabla_{\mathbf{p}(z')} F_b$$

$$\tau(z, z') = \int_{z'}^z \frac{dz''}{v_z(z'')}$$

THE PERTURBED DISTRIBUTION

- Putting all of this together, we can write the perturbed distribution function as

$$\begin{aligned} \delta \hat{f}_b(z, \mathbf{p}) = & \frac{e}{2c} \int_0^z dz' \frac{e^{i\omega\tau(z, z')}}{v_z(z')} \left\{ \left[-c p_z \frac{\partial}{\partial z} \delta \hat{\varphi} + i\omega (p_- \delta \hat{A}_+ + p_+ \delta \hat{A}_-) \right] \frac{1}{p} \frac{\partial}{\partial p} \right. \\ & + e^{i\Omega_0\tau(z')} \left(i\omega - v_z \frac{\partial}{\partial z} \right) \delta \hat{A}_+ \left(\frac{\partial}{\partial P_x} + i \frac{\partial}{\partial P_y} \right) \\ & \left. + e^{-i\Omega_0\tau(z')} \left(i\omega - v_z \frac{\partial}{\partial z} \right) \delta \hat{A}_- \left(\frac{\partial}{\partial P_x} - i \frac{\partial}{\partial P_y} \right) \right\} F_b(P_x, P_y, p) \end{aligned}$$

- This can be written as

$$\delta \hat{f}_b(z, \mathbf{p}) = \left[D_+ \left(\frac{\partial}{\partial P_x} + i \frac{\partial}{\partial P_y} \right) + D_- \left(\frac{\partial}{\partial P_x} - i \frac{\partial}{\partial P_y} \right) + D_z \frac{\partial}{\partial p} \right] F_b(P_x, P_y, p)$$

where

$$D_{\pm} = \frac{e}{2c} \int_z^{z'} dz' \frac{e^{i\omega\tau(z, z')}}{v_z(z')} e^{\pm i\Omega_0\tau(z')} \left(i\omega - v_z(z') \frac{\partial}{\partial z'} \right) \delta \hat{A}_{\pm}(z')$$

$$D_z = \frac{e}{2pc} \int_z^{z'} dz' \frac{e^{i\omega\tau(z, z')}}{v_z(z')} \left[-c p_z(z') \frac{\partial}{\partial z'} \delta \varphi(z') + i\omega (p_-(z') \hat{A}_+(z') + p_+(z') \hat{A}_-(z')) \right]$$

JACOBIAN OF THE TRANSFORMATION

- We also transform the integral over the constants of the motion

$$\int dp_x dp_y dp_z = \int dP_x dP_y dp \begin{vmatrix} \partial p_x / \partial P_x & \partial p_x / \partial P_y & \partial p_x / \partial p \\ \partial p_y / \partial P_x & \partial p_y / \partial P_y & \partial p_y / \partial p \\ \partial p_z / \partial P_x & \partial p_z / \partial P_y & \partial p_z / \partial p \end{vmatrix}$$

- The Jacobian of this transformation in the limit where $P_x = P_y = 0$ is

$$\begin{vmatrix} \partial p_x / \partial P_x & \partial p_x / \partial P_y & \partial p_x / \partial p \\ \partial p_y / \partial P_x & \partial p_y / \partial P_y & \partial p_y / \partial p \\ \partial p_z / \partial P_x & \partial p_z / \partial P_y & \partial p_z / \partial p \end{vmatrix}_{P_x = P_y = 0} = \begin{vmatrix} \cos \Omega_0 t & -\sin \Omega_0 t & \frac{\partial p_w}{\partial p} \cos k_w z \\ \sin \Omega_0 t & \cos \Omega_0 t & \frac{\partial p_w}{\partial p} \sin k_w z \\ -\frac{p_w}{p_z} \cos(k_w z - \Omega_0 t) & -\frac{p_w}{p_z} \sin(k_w z - \Omega_0 t) & \frac{1}{p_z} \left(p - p_w \frac{\partial p_w}{\partial p} \right) \end{vmatrix} = \frac{p}{p_z}$$

- As a result, the integral becomes

$$\int dp_x dp_y dp_z \delta(P_x) \delta(P_y) = \int dp \frac{p}{p_z}$$

THE SOURCE CURRENTS

- The perturbed source current in the rotating frame is

$$\delta \mathbf{J}(z, t) = [\delta \hat{J}_+(z) \hat{\mathbf{e}}_+ + \delta \hat{J}_-(z) \hat{\mathbf{e}}_- + \hat{J}_z(z) \hat{\mathbf{e}}_z] e^{-i\omega t} + c.c.$$

where

$$\begin{pmatrix} \delta \hat{J}_\pm(z) \\ \delta \hat{J}_z(z) \end{pmatrix} = - \frac{e}{m_e} \int dP_x dP_y dp \frac{p}{\gamma p_z} \delta \hat{f}_b(z, \mathbf{p}) \begin{pmatrix} p_\pm \\ p_z \end{pmatrix}$$

so that

$$\delta \hat{J}_\pm = \frac{en_b}{m_e} \int dP_x \delta(P_x) dP_y \delta(P_y) dp \frac{p}{\gamma} \left[\left(\frac{\partial}{\partial P_x} + i \frac{\partial}{\partial P_y} \right) \left(\frac{p_\pm}{p_z} D_+ \right) + \left(\frac{\partial}{\partial P_x} - i \frac{\partial}{\partial P_y} \right) \left(\frac{p_\pm}{p_z} D_- \right) - \frac{p_\pm}{p_z} D_z \frac{\partial}{\partial p} \right] G_b(p)$$

$$\delta \hat{J}_z = \frac{en_b}{m_e} \int dP_x \delta(P_x) dP_y \delta(P_y) dp \frac{p}{\gamma} \left[\left(\frac{\partial}{\partial P_x} + i \frac{\partial}{\partial P_y} \right) D_+ + \left(\frac{\partial}{\partial P_x} - i \frac{\partial}{\partial P_y} \right) D_- - D_z \frac{\partial}{\partial p} \right] G_b(p)$$

USEFUL DERIVATIVES

- There are a number of useful derivatives necessary in the evaluation of the $D_{\pm}$ and D_z operators

$$\frac{\partial p_{\pm}}{\partial P_x} = e^{\mp i\Omega_0\tau(z)} \quad \frac{\partial p_{\pm}}{\partial P_y} = \mp i e^{\mp i\Omega_0\tau(z)}$$

$$\longrightarrow \left(\frac{\partial}{\partial P_x} \pm i \frac{\partial}{\partial P_y} \right) p_{\pm} = 2e^{\mp i\Omega_0\tau(z)} \quad \left(\frac{\partial}{\partial P_x} \mp i \frac{\partial}{\partial P_y} \right) p_{\pm} = 0$$

$$\frac{\partial p_z}{\partial P_x} = - \frac{p_x \cos \Omega_0\tau(z) + p_y \sin \Omega_0\tau(z)}{p_z} \quad \frac{\partial p_z}{\partial P_y} = \frac{p_x \sin \Omega_0\tau(z) - p_y \cos \Omega_0\tau(z)}{p_z}$$

$$\longrightarrow \left(\frac{\partial}{\partial P_x} \pm i \frac{\partial}{\partial P_y} \right) \frac{1}{p_z} = e^{\mp i\Omega_0\tau(z)} \frac{p_{\mp}}{p_z^3}$$

Therefore

$$\left(\frac{\partial}{\partial P_x} \pm i \frac{\partial}{\partial P_y} \right) \frac{p_{\pm}}{p_z} = \frac{e^{\mp i\Omega_0\tau(z)}}{p_z} \left(2 + \frac{p_+ p_-}{p_z^2} \right) \quad \left(\frac{\partial}{\partial P_x} \mp i \frac{\partial}{\partial P_y} \right) \frac{p_{\pm}}{p_z} = e^{\pm i\Omega_0\tau(z)} \frac{p_{\pm}^2}{p_z^3}$$

THE $D_{\pm}$ AND D_z OPERATORS

$$\begin{aligned}
 D_{\pm} &= -\frac{e}{2c} \int_0^z dz' e^{\pm i\Omega_0 \tau(z')} \frac{d}{dz'} \left(e^{i\omega \tau(z, z')} \delta \hat{A}_{\pm}(z') \right) \\
 &= -\frac{e}{2c} \int_0^z dz' \frac{d}{dz'} \left(e^{i\omega \tau(z, z')} e^{\pm i\Omega_0 \tau(z')} \delta \hat{A}_{\pm}(z') \right) \\
 &\quad + \frac{e}{2c} \int_0^z dz' e^{i\omega \tau(z, z')} \delta \hat{A}_{\pm}(z') \frac{d}{dz'} \left(e^{\pm i\Omega_0 \tau(z')} \right) \\
 &= -\frac{e}{2c} \left(\delta \hat{A}_{\pm}(z) e^{\pm i\Omega_0 \tau(z)} - \delta \hat{A}_{\pm}(0) e^{i\omega \tau(z, 0)} e^{\pm i\Omega_0 t_0} \right) \\
 &\quad \pm \frac{ie\Omega_0}{2c} \int_0^z dz' \frac{e^{i\omega \tau(z, z')}}{v_z(z')} \delta \hat{A}_{\pm}(z') e^{\pm i\Omega_0 \tau(z')} \\
 \xrightarrow{P_x = P_y = 0} &= -\frac{e}{2c} e^{\pm i\Omega_0 t_0} \left(\delta \hat{A}_{\pm}(z) e^{\pm i\Omega_0 z/v_z} - \delta \hat{A}_{\pm}(0) e^{i\omega z/v_z} \right) \\
 &\quad \pm \frac{ie\Omega_0}{2cv_z} e^{\pm i\Omega_0 t_0} \int_0^z dz' e^{i\omega(z-z')/v_z} e^{\pm i\Omega_0 z'/v_z} \delta \hat{A}_{\pm}(z')
 \end{aligned}$$

$$\begin{aligned}
 D_z &= \frac{e}{2cp} \int_0^z dz' e^{i\omega(z-z')/v_z} \left[-\gamma m_e c \frac{\partial}{\partial z} \delta \hat{\varphi}(z') \right. \\
 &\quad \left. + i\omega \frac{p_w}{v_z} \left(e^{ik_w z'} \delta \hat{A}_+(z') + e^{-ik_w z'} \delta \hat{A}_-(z') \right) \right]
 \end{aligned}$$

THE $J_{\pm}$ SOURCE CURRENT

- The transverse rotational source current is

$$\delta \hat{J}_{\pm} = \frac{en_b}{m_e} \int dp \frac{p}{\gamma p_z} \left[e^{\mp i \Omega_0 \tau(z)} \left(2 + \frac{p_+ p_-}{p_z^2} \right) D_{\pm} + e^{\mp i \Omega_0 \tau(z)} \frac{p_{\pm}^2}{p_z^2} D_{\mp} \right. \\ \left. + p_{\pm} \left(\frac{\partial}{\partial P_x} + i \frac{\partial}{\partial P_y} \right) D_{+} + p_{\pm} \left(\frac{\partial}{\partial P_x} - i \frac{\partial}{\partial P_y} \right) D_{-} - p_{\pm} D_z \frac{\partial}{\partial p} \right]_{P_x=P_y=0} G_b(p)$$

where

$$e^{\mp i \Omega_0 \tau(z)} \left(2 + \frac{p_+ p_-}{p_z^2} \right) D_{\pm} = - \frac{e}{2c} \left(2 + \frac{p_w^2}{p_z^2} \right) \left[\delta \hat{A}_{\pm}(z) - \delta \hat{A}_{\pm}(0) e^{i(\omega \mp \Omega_0)z/v_z} \right] \\ \pm \frac{ie \Omega_0}{2c v_z} \left(2 + \frac{p_w^2}{p_z^2} \right) \int_0^z dz' e^{i(\omega \mp \Omega_0)(z-z')/v_z} \delta \hat{A}_{\pm}(z')$$

$$e^{\pm i \Omega_0 \tau(z)} \frac{p_{\pm}^2}{p_z^2} D_{\mp} = - \frac{e}{2c} \frac{p_w^2}{p_z^2} e^{\mp 2ik_w z} \left[\delta \hat{A}_{\mp}(z) - \delta \hat{A}_{\mp}(0) e^{i(\omega \pm \Omega_0)z/v_z} \right] \\ \mp \frac{ie \Omega_0}{2c v_z} \frac{p_w^2}{p_z^2} e^{\mp 2ik_w z} \int_0^z dz' e^{i(\omega \pm \Omega_0)(z-z')/v_z} \delta \hat{A}_{\mp}(z')$$

next

THE $J_{\pm}$ SOURCE CURRENT - 2

Additionally

$$\begin{aligned}
 p_{\pm} \left(\frac{\partial}{\partial P_x} + i \frac{\partial}{\partial P_y} \right) D_{+} = & -\frac{e}{2c} \frac{p_w^2}{p_z^2} \left[e^{i(k_w - \Omega_0/v_z)z} - 1 \right] \left[\frac{\Omega_0}{k_w v_z - \Omega_0} \delta \hat{A}_{+}(z) e^{i(\Omega_0/v_z \mp k_w)z} \right. \\
 & \left. - \frac{\omega}{k_w v_z - \Omega_0} \delta \hat{A}_{+}(0) e^{i(\omega/v_z \mp k_w)z} \right] \\
 & + \frac{ie\Omega_0}{2cv_z} \frac{p_w^2}{p_z^2} e^{i(\omega/v_z \mp k_w)z} \int_0^z dz' e^{-i(\omega/v_z - k_w)z'} \delta \hat{A}_{+}(z') \left\{ 1 + \frac{\omega}{k_w v_z - \Omega_0} \left[e^{i(k_w - \Omega_0/v_z)(z-z')} - 1 \right] \right. \\
 & \left. - \frac{\Omega_0}{k_w v_z - \Omega_0} \left[e^{-i(k_w - \Omega_0/v_z)z'} - 1 \right] \right\}
 \end{aligned}$$

$$\begin{aligned}
 p_{\pm} \left(\frac{\partial}{\partial P_x} - i \frac{\partial}{\partial P_y} \right) D_{-} = & -\frac{e}{2c} \frac{p_w^2}{p_z^2} \left[e^{-i(k_w - \Omega_0/v_z)z} - 1 \right] \left[\frac{\Omega_0}{k_w v_z - \Omega_0} \delta \hat{A}_{-}(z) e^{-i(\Omega_0/v_z \pm k_w)z} \right. \\
 & \left. + \frac{\omega}{k_w v_z - \Omega_0} \delta \hat{A}_{-}(0) e^{i(\omega/v_z \pm k_w)z} \right] \\
 & - \frac{ie\Omega_0}{2cv_z} \frac{p_w^2}{p_z^2} e^{i(\omega/v_z \mp k_w)z} \int_0^z dz' e^{-i(\omega/v_z + k_w)z'} \delta \hat{A}_{-}(z') \left\{ 1 - \frac{\omega}{k_w v_z - \Omega_0} \left[e^{-i(k_w - \Omega_0/v_z)(z-z')} - 1 \right] \right. \\
 & \left. - \frac{\Omega_0}{k_w v_z - \Omega_0} \left[e^{i(k_w - \Omega_0/v_z)z'} - 1 \right] \right\}
 \end{aligned}$$

THE J_z SOURCE CURRENT

- The axial source current is

$$\delta \hat{J}_z = \frac{en_b}{m_e} \int dp \frac{p}{\gamma} \left[\left(\frac{\partial}{\partial P_x} + i \frac{\partial}{\partial P_y} \right) D_+ + \left(\frac{\partial}{\partial P_x} - i \frac{\partial}{\partial P_y} \right) D_- - D_z \frac{\partial}{\partial p} \right] G_b$$

where

$$\begin{aligned} \left(\frac{\partial}{\partial P_x} \pm i \frac{\partial}{\partial P_y} \right) D_{\pm} = & -\frac{e}{2c} \frac{p_w}{p_z^2} \frac{e^{\pm i(k_w z - \Omega_0)z/v_z} - 1}{k_w z - \Omega_0} \left[\Omega_0 \delta \hat{A}_{\pm}(z) e^{\pm i \Omega_0 z/v_z} \right. \\ & \left. \mp \omega \delta \hat{A}_{\pm}(0) e^{i \omega z/v_z} \right] \\ & \pm \frac{ie}{2c} \frac{p_w}{p_z^2} \frac{\Omega_0}{v_z} e^{i \omega z/v_z} \int_0^z dz' e^{-i(\omega \mp k_w v_z)z'/v_z} \delta \hat{A}_{\pm}(z') \\ & \times \left[1 \pm \frac{\omega}{k_w v_z - \Omega_0} \left(e^{\pm i(k_w - \Omega_0/v_z)(z - z')} - 1 \right) \right. \\ & \left. \left. - \frac{\Omega_0}{k_w v_z - \Omega_0} \left(e^{\mp i(k_w - \Omega_0/v_z)z'} - 1 \right) \right] \right] \end{aligned}$$

THE LOW-GAIN REGIME

- We can recover the low-gain regime from this analysis where we assume that $B_0 = 0$, $\delta\hat{\varphi} = 0$, $\delta\hat{A}_- = 0$

$$\delta\hat{A}_+(z) = \delta\hat{A}_+(0)e^{i\int_0^z dz' k_+(z')}$$

$$k_+(z) = k_{0+} + \delta k(z) \quad | \delta k(z) | \ll | k_{0+} |$$

- This implies that

$$\begin{aligned} \left(2 + \frac{p_+ p_-}{p_z^2}\right) D_+ &= -\frac{e}{2c} \left(2 + \frac{p_w^2}{p_z^2}\right) \delta\hat{A}_+(z) (1 - e^{-i\psi_+}) \\ p_+ \left(\frac{\partial}{\partial P_x} + i \frac{\partial}{\partial P_y}\right) D_+ &= -\frac{e}{2c} \frac{p_w^2}{p_z^2} \frac{\omega}{k_w v_z} \delta\hat{A}_+(z) e^{-i\psi_+} (1 - e^{-ik_w z}) \\ p_+ D_z &= -\frac{e}{2c} \frac{p_w^2}{p_z^2} i \omega m_e \delta\hat{A}_+(z) e^{-i(\psi_+ + k_w z)} \int_0^z dz' e^{i(\psi_+ + k_w z')} \end{aligned}$$

$$\psi_+(z) = \int_0^z dz' \left(k_+ - \frac{\omega}{v_z} \right)$$

THE LOW-GAIN APPROXIMATIONS

- The phase ψ_+ and associated integrals are approximated as

$$\begin{aligned}\psi_+ &\approx (k_{0+} - \omega)z/v_z \\ \int_0^z dz' e^{i\psi_+} &\approx \frac{e^{i\psi_+} - 1}{i(k_{0+} - \omega/v_z)} \\ \int_0^z dz' e^{i(\psi_+ + k_w z)} &\approx \frac{e^{i(k_{0+} + k_w - \omega/v_z)z} - 1}{i(k_{0+} + k_w - \omega/v_z)}\end{aligned}$$

- The source current associated with the RHCP wave can now be written as

$$\begin{aligned}\delta\hat{J}_+ = & -\frac{\omega_b^2}{4\pi c} \int dp \left\{ \frac{p}{\gamma p_z} \left[\left(1 + \frac{p_w^2}{2p_z^2} \right) (1 - e^{-i\psi_+}) - \frac{p_w^2}{2p_z^2} \frac{\omega e^{-i\psi_+}}{k_w v_z} (1 - e^{-ik_w z}) \right] \right. \\ & \left. + \frac{p_w^2}{2p_z^2} \frac{m_e \omega v_z}{(k_{0+} + k_w) v_z} (1 - e^{-i(k_{0+} + k_w - \omega/v_z)z}) \frac{\partial}{\partial p} \right\} G_b(p) \delta\hat{A}_+(z)\end{aligned}$$

THE LOW-GAIN APPROXIMATIONS

- In the low-gain limit, the wave equation is approximately

$$\left(k_{0+}^2 - \frac{\omega^2}{c^2} + 2k_{0+}\delta k(z) \right) \delta \hat{A}_+(z) = \frac{4\pi}{c} \delta \hat{J}_+(z)$$

where we assume that

$$k_{0+}^2 \approx \omega^2/c^2$$

- As a result, the imaginary component of δk is

$$\begin{aligned} 2\text{Im}\delta k(z) \approx & -\frac{\omega_b^2}{\omega c} \int_0^\infty dp \left\{ m_e \omega \frac{p_w^2}{2p_{||}^2} \frac{\sin(\omega/v_z - k_{0+} - k_w)z}{\omega/v_z - k_{0+} - k_w} \frac{\partial}{\partial p} \right. \\ & - \frac{p}{\gamma p_{||}} \left[\left(1 + \frac{p_w^2}{2p_{||}^2} \right) \sin(\omega/v_z - k_{0+})z \right. \\ & \left. \left. + \frac{\omega}{k_w v_{||}} \frac{p_w^2}{2p_{||}^2} (\sin(\omega/v_z - k_{0+})z - \sin(\omega/v_z - k_{0+} - k_w)z) \right] \right\} G_b(p) \end{aligned}$$

THE SMALL-SIGNAL GAIN

- The power gain is defined as

$$G(L) = -2 \int_0^L dz \text{Im} \delta k(z)$$

- As a result [$\Theta = (\omega/v_{\parallel} - k_{0+} - k_w)L/2$],

$$G(L) = \frac{\omega_b^2}{\omega c} \int_0^\infty dp \left\{ \frac{m_e \omega L^2}{4} \frac{p_w^2}{p_{\parallel}^2} \left(\frac{\sin \Theta}{\Theta} \right)^2 \frac{\partial}{\partial p} \right. \\ \left. - \frac{Lp}{\gamma p_{\parallel}} \left[\left(1 + \frac{p_w^2}{2p_{\parallel}^2} \left[1 + \frac{\omega}{k_w v_{\parallel}} \right] \right) \frac{\sin^2 (\omega/v_{\parallel} - k_{0+})L/2}{(\omega/v_{\parallel} - k_{0+})L/2} - \frac{\omega}{k_w v_{\parallel}} \frac{p_w^2}{2p_{\parallel}^2} \frac{\sin^2 \Theta}{\Theta} \right] \right\} G_b(p)$$

- After integration by parts, this can be expressed as

$$G(L) = \frac{\omega_b^2}{\omega c} \int_0^\infty dp \left\{ -\frac{m_e \omega L^2}{4} \frac{\partial}{\partial p} \left[\frac{p_w^2}{p_{\parallel}^2} \left(\frac{\sin \Theta}{\Theta} \right)^2 \right] \right. \\ \left. - \frac{Lp}{\gamma p_{\parallel}} \left[\left(1 + \frac{p_w^2}{2p_{\parallel}^2} \left[1 + \frac{\omega}{k_w v_{\parallel}} \right] \right) \frac{\sin^2 (\omega/v_{\parallel} - k_{0+})L/2}{(\omega/v_{\parallel} - k_{0+})L/2} - \frac{\omega}{k_w v_{\parallel}} \frac{p_w^2}{2p_{\parallel}^2} \frac{\sin^2 \Theta}{\Theta} \right] \right\} G_b(p)$$

THE SMALL-SIGNAL GAIN

- Noting the following derivatives

$$\frac{\partial}{\partial p} \left(\frac{p_w^2}{p_{||}^2} \right) = \frac{p_w^2}{p_{||}^2} \frac{p}{p_{||}^2} \quad \frac{\partial}{\partial p} = - \frac{m_e \omega L}{2 v_{||}} \frac{p}{\gamma_{||}^2 p_{||}^2} \frac{\partial}{\partial \Theta}$$

- We obtain the small-signal gain in the form

$$G(L) = \frac{\omega_b^2}{\omega c} \int_0^\infty dp \frac{p}{\gamma p_{||}} G_b(p) \left\{ \frac{\omega^2 L^3}{\gamma_{||}^2 v_{||}^2} \frac{p_w^2}{8 p_{||}^2} \frac{\partial}{\partial p} \left(\frac{\sin \Theta}{\Theta} \right)^2 \right. \\ \left. + \frac{p_w^2}{2 p_{||}^2} \frac{\omega L}{k_w v_{||}} (k_w L + \Theta) \left(\frac{\sin \Theta}{\Theta} \right)^2 - L \left(1 + \frac{p_w^2}{2 p_{||}^2} \frac{\omega}{k_w v_{||}} \right) \frac{\sin^2 (\Theta + k_w v_{||})}{\Theta + k_w v_{||}} \right\}$$

- Using a mono-energetic distribution

$$G_b(p) = \frac{p_{||}}{p} \delta(p - p_0)$$

- We recover the small-signal gain formula

$$G(L) \approx \frac{\omega_b^2 L^3 k}{8 \gamma \gamma_{||}^2 v_{||}^2} \frac{p_w^2}{p_{||}^2} \frac{\partial}{\partial \Theta} \left(\frac{\sin \Theta}{\Theta} \right)^2$$

THE HIGH-GAIN REGIME

- In the high-gain regime, we assume that the perturbed fields vary as

$$\delta\hat{A}_{\pm}(z) = \delta\hat{A}_{k_{\pm}}(0)e^{ik_{\pm}z} \quad \delta\hat{\varphi}_k(z) = \delta\hat{\varphi}_k(0)e^{ikz}$$

- The strongest coupling is between $k = k_{\pm} \mp k_w$, so that we retain only the lowest order coupling terms, and obtain

$$\begin{aligned} \left(\frac{\partial}{\partial P_x} \pm i \frac{\partial}{\partial P_y}\right) D_{\pm} &\approx \frac{e}{2cp_z} \frac{p_w}{p_z} \delta\hat{A}_{\pm}(z) e^{\pm ik_w z} \frac{\Omega_0}{k_w v_z - \Omega_0} \left(\frac{\omega \mp k_w v_z}{\omega \mp k_w v_z - k_{\pm} v_z} + \frac{\omega}{\omega \mp \Omega_0 - k_{\pm} v_z} \right) \\ \frac{p_{\pm}}{p_z} \left(\frac{\partial}{\partial P_x} \pm i \frac{\partial}{\partial P_y}\right) D_{\pm} &\approx \frac{e}{2cp_z} \frac{p_w^2}{p_z^2} \delta\hat{A}_{\pm}(z) \frac{\Omega_0}{k_w v_z - \Omega_0} \left[\frac{\omega \mp k_w v_z}{\omega \mp k_w v_z - k_{\pm} v_z} - \frac{\omega}{\omega \mp \Omega_0 - k_{\pm} v_z} \right] \\ \frac{e^{\mp i\Omega_0 \tau(z)}}{p_z} \left(2 + \frac{p_+ p_-}{p_z^2}\right) D_{\pm} &\approx -\frac{e}{2cp_z} \left(2 + \frac{p_w^2}{p_z^2}\right) \frac{\omega - k_{\pm} v_z}{\omega \mp \Omega_0 - k_{\pm} v_z} \delta\hat{A}_{\pm}(z) \\ \frac{e^{\pm i\Omega_0 \tau(z)}}{p_z} \frac{p_{\pm}^2}{p_z^2} D_{\mp} &\approx 0 \quad \frac{p_{\pm}}{p_z} \left(\frac{\partial}{\partial P_x} \mp i \frac{\partial}{\partial P_y}\right) D_{\mp} \approx 0 \\ \frac{p_{\pm}}{p_z} D_z &\approx -\frac{e}{2c} \frac{p_z}{p} \frac{p_w}{p_z} \left[\frac{p_w}{p_w} \frac{\omega \delta\hat{A}_{\pm}(z)}{\omega \mp k_w v_z - k_{\pm} v_z} - \frac{ck \delta\hat{\varphi}(z) e^{\mp ik_w z}}{\omega - kv_z} \right] \\ D_z &\approx -\frac{e}{2cp} \frac{p_z}{p} \frac{kc}{\omega - kv_z} \delta\hat{\varphi}(z) - \frac{e}{2cp_z} \omega \frac{p_w}{p_z} \left[\frac{\delta\hat{A}_+(z) e^{ik_w z}}{\omega - (k_+ + k_w) v_z} + \frac{\delta\hat{A}_-(z) e^{-ik_w z}}{\omega - (k_- - k_w) v_z} \right] \end{aligned}$$

THE SOURCE CURRENTS

- The source currents can now be written in the form

$$\begin{aligned}
 \delta \hat{J}_{\pm}(z) \approx & -\frac{\omega_b^2}{8\pi c} \delta \hat{A}_{\pm}(z) \int_0^{\infty} dp \frac{p}{\gamma p_z} G_b(p) \left[\frac{2(\omega - k_{\pm} v_z)}{\omega \mp \Omega_0 - k_{\pm} v_z} + \frac{p_w^2}{p_z^2} \right. \\
 & \left. + \frac{p_w^2}{p_z^2} \frac{\Omega_0}{k_w v_z - \Omega_0} \left(\frac{\omega \mp \Omega_0 \pm k_w v_z}{\omega \mp \Omega_0 - k_{\pm} v_z} - \frac{\omega \mp k_w v_z}{\omega \mp k_w v_z - k_{\pm} v_z} \right) \right] \\
 & + \frac{\omega_b^2}{8\pi c} \delta \hat{A}_{\pm}(z) \int_0^{\infty} dp \frac{\omega m_e v_z}{\omega \mp k_w v_z - k_{\pm} v_z} \frac{p_w^2}{p_z^2} \frac{\partial}{\partial p} G_b(p) \\
 & - \frac{\omega_b^2}{8\pi} \delta \hat{\varphi}(z) e^{\mp i k_w z} \int_0^{\infty} dp \frac{k m_e v_z}{\omega - k v_z} \frac{p_w^2}{p_z^2} \frac{\partial}{\partial p} G_b(p) \\
 \delta \hat{J}_z(z) \approx & -\frac{\omega_b^2}{8\pi} \delta \hat{\varphi}(z) \int_0^{\infty} dp \frac{k m_e v_z}{\omega - k v_z} \frac{\partial}{\partial p} G_b(p) \\
 & + \frac{\omega_b^2}{8\pi c} \delta \hat{A}_+(z) e^{i k_w z} \int_0^{\infty} dp \frac{p}{\gamma p_z} \frac{p_w^2}{p_z^2} \left[\frac{\Omega_0}{k_w v_z - \Omega_0} \left(\frac{\omega - k_w v_z}{\omega - (k_+ + k_w) v_z} - \frac{\omega}{\omega - \Omega_0 - k_+ v_z} \right) \right. \\
 & \left. + \frac{\omega}{\omega - (k_+ + k_w) v_z} \frac{p_z^2}{p} \frac{\partial}{\partial p} \right] G_b(p) \\
 & + \frac{\omega_b^2}{8\pi c} \delta \hat{A}_-(z) e^{-i k_w z} \int_0^{\infty} dp \frac{p}{\gamma p_z} \frac{p_w^2}{p_z^2} \left[\frac{\Omega_0}{k_w v_z - \Omega_0} \left(\frac{\omega + k_w v_z}{\omega - (k_- - k_w) v_z} - \frac{\omega}{\omega + \Omega_0 - k_- v_z} \right) \right. \\
 & \left. + \frac{\omega}{\omega - (k_- - k_w) v_z} \frac{p_z^2}{p} \frac{\partial}{\partial p} \right] G_b(p)
 \end{aligned}$$

THE TRANSVERSE CURRENT

- The transverse source current can now be shown as

$$\delta\hat{J}_{\pm}(z) = -\frac{\omega_b^2}{8\pi c} \delta\hat{A}_{\pm}(z) \left[2 \left\langle \frac{p}{\gamma p_{\parallel}} \frac{\omega - k_{\pm} v_z}{\omega - \Omega_0 - k_{\pm} v_z} \right\rangle + K^2 S_{\pm}(k_{\pm}, \omega) \right] - K \frac{ck^2}{8\pi} \delta\hat{\varphi}(z) e^{\mp i k_w z} \chi_a(k, \omega)$$

where

$$\langle (\dots) \rangle = \int_0^{\infty} dp G_b(p) (\dots)$$

$$\begin{aligned} S_{\pm}(k_{\pm}, \omega) = & \int_0^{\infty} dp \frac{p}{\gamma^3 p_{\parallel}} G_b(p) \frac{k_w^2 c^2}{(k_w v_{\parallel} - \Omega_0)^2} \left[1 + \frac{\Omega_0}{k_w v_{\parallel} - \Omega_0} \right. \\ & \times \left. \left(\frac{\omega \mp \Omega_0 + k_w v_{\parallel}}{\omega \mp \Omega_0 - k_{\pm} v_{\parallel}} - \frac{\omega \mp k_w v_{\parallel}}{\omega \mp k_w v_{\parallel} - k_{\pm} v_{\parallel}} \right) \right] \\ & - m_e c^2 \int_0^{\infty} dp \frac{k_w^2 v_{\parallel}}{\gamma^2 (k_w v_{\parallel} - \Omega_0)^2} \frac{\omega}{\omega \mp k_w v_{\parallel} - k_{\pm} v_{\parallel}} \frac{\partial}{\partial p} G_b(p) \\ \chi_a(k, \omega) = & \frac{\omega_b^2}{k} \int_0^{\infty} dp \frac{k_w v_{\parallel}}{k_w v_{\parallel} - \Omega_0} \frac{m_e}{\gamma(\omega - k v_{\parallel})} \frac{\partial}{\partial p} G_b(p) \end{aligned}$$

THE AXIAL CURRENT

- The axial perturbed current can be expressed as

$$\delta J_z(z) = -\frac{\omega k}{8\pi} \delta \hat{\varphi}(z) \chi(k, \omega) - \frac{\omega k_w K}{8\pi} \left[\delta \hat{A}_+(z) e^{ik_w z} \sigma_+(k_+, \omega) + \delta \hat{A}_-(z) e^{-ik_w z} \sigma_-(k_-, \omega) \right]$$

where

$$\chi(k, \omega) = \frac{\omega_b^2}{k} \int_0^\infty dp \frac{m_e}{\omega - k v_{||}} \frac{\partial}{\partial p} G_b(p)$$

$$\begin{aligned} \sigma_\pm(k_\pm, \omega) = & \frac{\omega_b^2}{\omega} \int_0^\infty dp \frac{p}{\gamma^2 p_{||}} G_b(p) \frac{\Omega_0}{(\Omega_0 - k_w v_{||})} \\ & \times \left(\frac{\omega \mp k_w v_{||}}{\omega \mp k_w v_{||} - k_\pm v_{||}} - \frac{\omega}{\omega \mp \Omega_0 - k_\pm v_{||}} \right) \\ & + \frac{\omega_b^2}{\omega} \int_0^\infty dp \frac{\omega}{\gamma(k_w v_{||} - \Omega_0)} \frac{m_e v_{||}}{\omega \mp k_w v_{||} - k_\pm v_{||}} \frac{\partial}{\partial p} G_b(p) \end{aligned}$$

THE COUPLED EQUATIONS

- We can now write two coupled equations for the left- and right-hand circularly polarized vector potentials and the scalar potential

$$\Lambda_{\pm}(k_{\mp}, \omega) \delta \hat{A}_{\pm}(0) + \frac{K}{2} \frac{c^2 k^2}{\omega^2} \chi_a(k, \omega) \delta \hat{\varphi}(0) = 0$$

$$\frac{K}{2} \frac{k_w}{k} [\sigma_+(k_-, \omega) \delta \hat{A}_+(0) + \sigma_-(k_+, \omega) \delta \hat{A}_-(0)] + \frac{K}{2} [1 + \chi(k, \omega)] \delta \hat{\varphi}(0) = 0$$

$$\Lambda_{\pm}(k_{\mp}, \omega) = 1 - \frac{c^2 k_{\pm}^2}{\omega^2} - \frac{\omega_b^2}{\omega^2} \left\langle \frac{p}{\gamma p_{\parallel}} \frac{\omega - k_{\pm} v_{\parallel}}{\omega \mp \Omega_0 - k_{\pm} v_{\parallel}} \right\rangle - \frac{\omega_b^2 K^2}{2\omega^2} S_{\pm}(k_{\pm}, \omega)$$

- In the absence of the coupling between the electromagnetic and electrostatic waves (i.e., $K = 0$)

$$\Lambda_{\pm}(k_{\mp}, \omega) = 0 \quad \longrightarrow \quad \text{Dispersion equation for the electromagnetic waves}$$

$$1 + \chi(k, \omega) = 0 \quad \longrightarrow \quad \text{Dispersion equation for the electrostatic waves}$$

THE GENERAL DISPERSION EQUATION

- The general dispersion equation describes the coupling between the electromagnetic and electrostatic waves. For a monoenergetic distribution it is of the form

$$\left[(\omega - kv_{\parallel})^2 - \frac{\omega_b^2}{\gamma_0 \gamma_{\parallel}^2} \Phi \right] = - \frac{v_w^2}{2v_{\parallel}^2} \frac{\omega_b^2}{\gamma_0} \left[\frac{\alpha_+(k_+, \omega)}{\varepsilon_+(k_+, \omega)} + \frac{\alpha_-(k_-, \omega)}{\varepsilon_-(k_-, \omega)} \right]$$

Electrostatic wave

$= d\gamma/dv_{\parallel}$ → Unstable when $\Phi < 0$

LHCP wave

RHCP wave

- In the absence of an axial magnetic field, the dispersion equation is simplified, where $\Phi = 0$, and

$$\varepsilon_{\pm}(k_{\pm}, \omega) = 1 - \frac{\omega_b^2}{\gamma_0 (\omega^2 - k_{\pm}^2 c^2)}$$

$$\alpha_{\pm}(k_{\pm}, \omega) = \frac{\beta_{\parallel}^2}{(\omega^2 - k_{\pm}^2 c^2)} \left[\omega^2 - k^2 c^2 - \frac{\omega_b^2}{\gamma_0} + \frac{\omega_b^2}{\gamma_0 (\omega - kv_{\parallel})^2} \right]$$

THE REDUCED DISPERSION EQUATION

- If we consider the RHCP mode, then $|\varepsilon_+(k_+, \omega)| \ll |\varepsilon_-(k_-, \omega)|$ and $\omega_b^2/\gamma_0 \ll \omega^2$, then the dispersion equation becomes ($k_+ = k - k_w$)

$$\left[(\omega - kv_{\parallel})^2 - \frac{\omega_b^2}{\gamma_0 \gamma_{\parallel}^2} \right] \left(\omega^2 - k_+^2 c^2 - \frac{\omega_b^2}{\gamma_0} \right) \approx - \frac{v_w^2}{2c^2} \frac{\omega_b^2}{\gamma_0} \left(\omega^2 - k^2 c^2 - \frac{\omega_b^2}{\gamma_0} \right)$$

$$= \left(\omega - \sqrt{k_+^2 c^2 + \frac{\omega_b^2}{\gamma_0}} \right) \left(\omega + \sqrt{k_+^2 c^2 + \frac{\omega_b^2}{\gamma_0}} \right)$$

Forward propagating wave
Backward propagating wave

$$= \left(\omega - kv_{\parallel} - \frac{\omega_b}{\gamma_0^{1/2} \gamma_{\parallel}} \right) \left(\omega - kv_{\parallel} + \frac{\omega_b}{\gamma_0^{1/2} \gamma_{\parallel}} \right)$$

Positive-energy space-charge wave
Negative-energy space-charge wave

GRAPHICAL REPRESENTATION

- The interaction that leads to growth is between the forward-propagating electromagnetic wave and the negative energy space-charge wave
- The coupled-wave dispersion equation deforms as shown in the figure below

THE QUARTIC DISPERSION EQUATION

- The RHS of the previous dispersion equation can be simplified as follows

$$\begin{aligned}
 \left(\omega^2 - c^2 k^2 - \frac{\omega_b^2}{\gamma_0} \right) &= \omega^2 - c^2 (k_+ + k_w)^2 - \frac{\omega_b^2}{\gamma_0} \\
 &\approx 0 \\
 &= \left(\omega^2 - c^2 k_+^2 - \frac{\omega_b^2}{\gamma_0} \right) - c^2 (2k_+ k_w + k_w^2) \\
 &\approx \omega/c \approx \omega/v_{\parallel} \\
 &\approx -c^2 k_w (k_+ + [k_+ + k_w]) \\
 &\approx -\frac{k_w c^2 \omega}{v_{\parallel}} (1 + \beta_{\parallel}) \approx -\frac{\omega^2}{\beta_{\parallel}^2 \gamma_{\parallel}^2}
 \end{aligned}$$

- As a result, the dispersion equation reduces to a quartic polynomial

$$\left[(\omega - k v_{\parallel})^2 - \frac{\omega_b^2}{\gamma_0 \gamma_{\parallel}^2} \right] \left(\omega^2 - c^2 k_+^2 - \frac{\omega_b^2}{\gamma_0} \right) \approx \frac{v_w^2}{2 v_{\parallel}^2} \frac{\omega_b^2 \omega^2}{\gamma_0 \gamma_{\parallel}^2}$$

THE PIERCE DISPERSION EQUATION

- We focus on forward propagating waves that grow spatially as they propagate (*i.e.*, we look for complex solutions for k_+ given a real value for ω) so that

$$\omega^2 - c^2 k_+^2 - \frac{\omega_b^2}{\gamma_0} \approx -2c^2 k_+ (k_+ - K) \quad \leftarrow \quad K^2 \equiv \frac{\omega^2}{c^2} - \frac{\omega_b^2}{\gamma_0 c^2}$$

- Defining a perturbed wavenumber

$$\delta k = k - \frac{\omega}{v_{\parallel}} - \frac{\omega_b}{\gamma_0^{1/2} \gamma_{\parallel} v_{\parallel}}$$

We obtain the cubic Pierce dispersion equation

$$\delta k \left(\delta k + \frac{2\omega_b}{\gamma_0^{1/2} \gamma_{\parallel} v_{\parallel}} \right) (\delta k - \Delta k) = - \frac{v_w^2}{2c^2} \frac{\omega_b^2}{\gamma_0 c^2 k_w^2} k_w^3 = - (2\rho k_w)^3$$

where

$$k \equiv k_w + K - \frac{\omega}{v_{\parallel}} - \frac{\omega_b}{\gamma_0^{1/2} \gamma_{\parallel} v_{\parallel}}$$

THE HIGH-GAIN COMPTON REGIME

- The ponderomotive potential is dominant over the space-charge potential in the high-gain Compton regime, and this requires that

$$|\delta k| \gg \frac{2\omega_b}{\gamma_0^{1/2} \gamma_{\parallel} v_{\parallel}}$$

- The dispersion equation then becomes

$$k^2(\delta k - \Delta k) = -\frac{v_w^2}{2c^2} \frac{\omega_b^2}{\gamma_0 c^2 k_w^2} k_w^3 = -(2\rho k_w)^3$$

- The maximum growth rate is found for zero detuning ($\Delta k = 0$) for which

$$\frac{\delta k}{k_w} = \frac{1 \pm i\sqrt{3}}{2} \left(\frac{v_w^2}{2c^2} \frac{\omega_b^2}{\gamma_0 c^2 k_w^2} \right)^{1/3}$$

This detuning is in contrast to what is found in the low-gain regime

- As a result, the criterion for the high-gain Compton regime can be written as

$$\frac{\omega_b}{\gamma_0^{1/2} \gamma_{\parallel} c k_w} \ll \frac{1}{16} \frac{v_w^2}{c^2} \gamma_{\parallel}^2 = \frac{1}{16} \frac{K^2}{1 + K^2}$$

THE HIGH-GAIN RAMAN REGIME

- The space-charge potential dominates over the ponderomotive potential in this regime and we find that the dispersion equation reduces to a quadratic equation

$$\delta k(\delta k - \Delta k) = - \frac{v_w^2}{4c^2} \frac{\omega_b}{\gamma_0^{1/2} c k_w} k_w^2$$

- As in the high-gain Compton regime, the maximum gain is found for zero detuning, for which

$$\frac{\delta k}{k_w} = i \frac{v_w^2}{2v_{||}^2} \left(\frac{\omega_b}{\gamma_0^{1/2} c k_w} \right)^{1/2}$$

- The Raman regime is not generally important for short wavelength FELs

THE INCLUSION OF AN AXIAL FIELD

- The more general form of the dispersion equation including the effect of an axial magnetic field is

$$\delta k \left(\delta k + \frac{2\omega_b}{\gamma_0^{1/2} \gamma_{\parallel} v_{\parallel}} \Phi^{1/2} \right) (\delta k - \Delta K) = - \frac{v_w^2}{2v_{\parallel}^2} \frac{\omega_b^2}{\gamma_0 c^2 k_w^2} k_w^3 \Phi$$

$$\frac{v_w}{v_{\parallel}} = \frac{\Omega_w}{\Omega_0 - k_w v_{\parallel}}$$

$$\frac{d}{d\gamma} v_{\parallel} = \frac{c^2}{\gamma \gamma_{\parallel}^2 v_{\parallel}} \Phi(\lambda_0)$$

SLIPPAGE IN THE HIGH-GAIN REGIME

- Slippage is reduced in the high-gain regime because the group velocity of the light is reduced

$$\kappa^2 v_{\parallel}^2 = \omega_b^2 / \gamma_0 \gamma_{\parallel}^2 \quad \leftarrow \quad \left[(\omega - k v_{\parallel})^2 - \kappa^2 v_{\parallel}^2 \right] \left(\omega^2 - c^2 k_+^2 - \frac{\omega_b^2}{\gamma_0} \right) = \frac{\beta_w^2}{2} \frac{\omega_b^2}{\gamma_0 \gamma_{\parallel}^2} \omega^2 \quad \rightarrow \quad \beta_w^2 = v_w^2 / v_{\parallel}^2$$

- The group velocity $v_{gr} (= \partial \omega / \partial k_+)$ can be found by taking implicit differentiation of the dispersion equation which yields

$$\begin{aligned} & \left\{ \omega \left[(\omega - k v_{\parallel})^2 - \kappa^2 v_{\parallel}^2 \right] + (\omega - k v_{\parallel}) \left(\omega^2 - c^2 k_+^2 - \frac{\omega_b^2}{\gamma_0} \right) - \frac{\beta_w^2}{2} \frac{\omega_b^2}{\gamma_0 \gamma_{\parallel}^2} \omega \right\} \left(\frac{1}{c} \frac{\partial \omega}{\partial k_+} \right) = \\ & = \left\{ \left[(\omega - k v_{\parallel})^2 - \kappa^2 v_{\parallel}^2 \right] c k_+ + \beta_{\parallel} (\omega - k v_{\parallel}) \left(\omega^2 - c^2 k_+^2 - \frac{\omega_b^2}{\gamma_0} \right) \right\} \end{aligned}$$

THE GROUP VELOCITY

- We note that

$$\begin{aligned} \left[(\omega - kv_{\parallel})^2 - \kappa^2 v_{\parallel}^2 \right] &= [(\omega - kv_{\parallel}) - \kappa v_{\parallel}][(\omega - kv_{\parallel}) + \kappa v_{\parallel}] \\ &= v_{\parallel}^2 (\omega/v_{\parallel} - k + \kappa)(\omega/v_{\parallel} - k - \kappa) = v_{\parallel}^2 \delta k (\delta k + 2\kappa) \end{aligned}$$

$$(\omega - kv_{\parallel}) = -v_{\parallel}(k - \omega/v_{\parallel}) = -v_{\parallel}(\delta k + \kappa)$$

$$\begin{aligned} \left(\omega^2 - c^2 k_+^2 - \frac{\omega_b^2}{\gamma_0} \right) &= -2c^2 k_+(k_+ - K) = -2c^2 k_+(k_+ + k_w - K - k_w) \\ &= -2c^2 k_+(k - \omega/v_{\parallel} - \kappa - K - k_w + \kappa + \omega/v_{\parallel}) = -2c^2 k_+(\delta k - \Delta k) \end{aligned}$$

- As a result

$$\omega v_{\parallel}^2 \left[\delta k (\delta k + 2\kappa) + \frac{2}{\beta_{\parallel}} \frac{ck_+}{\omega} (\delta k - \Delta k)(\delta k + \kappa) - \left(\frac{\beta_w^2}{2} \frac{\omega_b^2}{\gamma_0 c^2} \right) \frac{1}{\gamma_{\parallel}^2 \beta_{\parallel}^2} \right] \left(\frac{v_{gr}}{c} \right) =$$

$$= ck_+ v_{\parallel}^2 [\delta k (\delta k + 2\kappa) - 2(\delta k - \Delta k)(\delta k + \kappa)]$$

- So that

$$\begin{aligned} \left[\delta k (\delta k + 2\kappa) + \frac{2}{\beta_{\parallel}} \frac{ck_+}{\omega} (\delta k - \Delta k)(\delta k + \kappa) + \frac{\delta k}{\gamma_{\parallel}^2 \beta_{\parallel} k_w} (\delta k + 2\kappa)(\delta k - \Delta k) \right] \left(\frac{v_{gr}}{c} \right) = \\ = \frac{ck_+}{\omega} [\delta k (\delta k + 2\kappa) - 2(\delta k - \Delta k)(\delta k + \kappa)] \end{aligned}$$

THE GROUP VELOCITY & SLIPPAGE

- At the peak in the growth rate (on-resonance where $\Delta k = 0$) in the high-gain Compton regime ($|\delta k| \gg \kappa$), and where $\omega \approx ck_+$

$$\left[\left(1 + \frac{2}{\beta_{\parallel}} \right) \delta k^2 + \frac{\delta k^3}{\gamma_{\parallel}^2 \beta_{\parallel} k_w} \right] \left(\frac{v_{gr}}{c} \right) = 3 \delta k^2$$

neglect

$$\begin{aligned} &= 3 - 2 \left(1 - \frac{1}{\beta_{\parallel}} \right) = 3 \left[1 - \frac{2}{3} \left(1 - \frac{1}{\beta_{\parallel}} \right) \right] = 3 \left[1 - \frac{2}{3} \frac{1 - \beta_{\parallel}}{\beta_{\parallel}} \right] \\ &= 3 \left[1 - \frac{2}{3 \gamma_{\parallel}^2 \beta_{\parallel} (1 + \beta_{\parallel})} \right] \approx 3 \left(1 + \frac{1}{3 \gamma_{\parallel}^2} \right) \end{aligned}$$

$$\longrightarrow \frac{v_{gr}}{c} \approx \left(1 - \frac{1}{3 \gamma_{\parallel}^2} \right)$$

- The slippage distance, s , over a wiggler of length L_w is

$$s = c L_w \left(\frac{1}{v_{\parallel}} - \frac{1}{v_{gr}} \right) \approx \frac{c L_w}{v_{\parallel}} \left(1 - \frac{v_{\parallel}}{v_{gr}} \right) = \frac{c L_w}{v_{\parallel}} \left(1 - \frac{v_{\parallel}}{c} \left[1 + \frac{1}{3 \gamma_{\parallel}^2} \right] \right) = \frac{c L_w}{v_{\parallel}} \left(1 - \beta_{\parallel} - \frac{\beta_{\parallel}}{3 \gamma_{\parallel}^2} \right)$$

$$\approx L_w \left(\frac{1}{2 \gamma_{\parallel}^2} - \frac{1}{3 \gamma_{\parallel}^2} \right) = \frac{N_w \lambda_w}{6 \gamma_{\parallel}^2} \approx \frac{N_w \lambda_w}{3} \longrightarrow 1/3^{\text{rd}} \text{ the usual slippage definition}$$

THERMAL EFFECTS

- The resonance condition $\omega = (k + k_w)v_{\parallel}$ implies that thermal effects becomes important when $\Delta v_{\parallel}(\text{Re } k + k_w) \approx v_{\parallel} \text{Im } k$, or

$$\frac{\Delta v_{\parallel}}{v_{\parallel}} \approx \frac{\text{Im } k}{\text{Re } k + k_w}$$

- High-Gain Compton Regime

$$\begin{aligned} \text{Im } k &= \frac{\sqrt{3}k_w}{2} \left(\frac{\beta_w^2}{2} \frac{\omega_b^2}{\gamma_0 c^2 k_w^2} \right)^{1/3} \\ \text{Re } k &= 2\gamma_{\parallel}^2 k_w \end{aligned} \quad \longrightarrow \quad \frac{\Delta v_{\parallel}}{v_{\parallel}} \approx \frac{\sqrt{3}}{4\gamma_{\parallel}^2} \left(\frac{\beta_w^2}{2} \frac{\omega_b^2}{\gamma_0 c^2 k_w^2} \right)^{1/3}$$

- High-Gain Raman Regime

$$\text{Im } k \approx \frac{\beta_w}{2} \left(\frac{\omega_b^2}{\gamma_0 c^2 k_w^2} \right)^{1/4} \quad \longrightarrow \quad \frac{\Delta v_{\parallel}}{v_{\parallel}} \approx \frac{\beta_w}{4\gamma_{\parallel}^2} \left(\frac{\omega_b^2}{\gamma_0 c^2 k_w^2} \right)^{1/4}$$

THE PITCH-ANGLE DISTRIBUTION

- We consider a mono-energetic distribution with a pitch-angle spread, which provides for an axial energy spread

$$F_b(P_x, P_y, p) = n_b G_{\perp}(P_x, P_y) \frac{p_z}{p} \delta(p - p_0) \quad G_{\perp}(P_x, P_y) = \frac{1}{\pi \Delta P^2} e^{-(P_x^2 + P_y^2)/\Delta P^2}$$

- The axial momentum is given approximately by

$$p_z \approx \sqrt{p_0^2 - p_w^2 - P_{\perp}^2}$$

$$\begin{aligned} \longrightarrow \Delta p_z &\approx \sqrt{p_0^2 - p_w^2} - \sqrt{p_0^2 - p_w^2 - P_{\perp}^2} \approx \sqrt{p_0^2 - p_w^2} \left(1 - \sqrt{1 - \frac{P_{\perp}^2}{p_0^2 - p_w^2}} \right) \\ &\approx \frac{\Delta P^2}{2 \sqrt{p_0^2 - p_w^2}} \approx \frac{\Delta P^2}{2 p_0} \end{aligned}$$

- The axial velocity spread, therefore, becomes

$$\frac{\Delta v_z}{v_z} \approx \frac{\Delta P^2}{2 p_0^2}$$

Thermal effects are important when

$$\longrightarrow \frac{\Delta P^2}{p_0^2} \approx \frac{\sqrt{3}}{2 \gamma_z^2} \left(\frac{\beta_w^2}{2} \frac{\omega_b^2}{\gamma_0 c^2 k_w^2} \right)^{1/3}$$

THE DISPERSION EQUATION

- The dispersion equation associated with the pitch-angle distribution can be shown to be [Freund & Antonsen, *Principles of Free-Electron Lasers*, Chapman & Hall, London, 1996, . 115]Chap. 4, p

$$\left[\left(\omega - k v_{\parallel} \right)^2 - \frac{\omega_b^2}{\gamma_0 \gamma_{\parallel}^2} T(\xi) \right] \left(\omega^2 - c^2 k_{+}^2 - \frac{\omega_b^2}{\gamma_0} \right) = - \frac{\omega_b^2 K^2}{2 \gamma_0 \gamma_0^2} T(\xi) \left(\omega^2 - c^2 k^2 - \frac{\omega_b^2}{\gamma_0} T(\xi) \right)$$

where the thermal function $T(\xi)$ is written in terms of the Exponential Integral function. Note that this is NOT the Plasma Dispersion Function.

$$T(\xi) = \xi \left[1 - \xi e^{\xi} E_1(\xi) \right]$$

$$\xi = \frac{\gamma_0^2 m_e}{\Delta P^2} \left(\frac{\omega^2}{k^2} - v_{\parallel}^2 \right)$$

$$E_1(\xi) = \int_{\xi}^{\infty} dt \frac{e^{-t}}{t}$$

VARIATION WITH ENERGY SPREAD

- Numerical solution of the dispersion equation is shown in the figure below for a set of parameters shown in the figure.
- The solution indicates that $\text{Im } k/k_w \approx 0.011$, and that $\text{Re } k/k_w + 1 \approx 15.4$ so that

$$\frac{\Delta v_{\parallel}}{v_{\parallel}} \approx \frac{\text{Im } k}{\text{Re } k + k_w} \approx 0.037$$

The growth rate is relatively flat until thermal effects *kick in*