LA-UR-13-28316

Approved for public release; distribution is unlimited.

Title: TSA Radiation Portal Monitor SC-770 Telnet Connection Using Tera Term

Author(s): Byers, Loren W.

Intended for: Report

Issued: 2013-10-29

Disclaimer:

Los Alamos National Laboratory, an affirmative action/equal opportunity employer, is operated by the Los Alamos National Security, LLC for the National Nuclear Security Administration of the U.S. Department of Energy under contract DE-AC52-06NA25396. By approving this article, the publisher recognizes that the U.S. Government retains nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or to allow others to do so, for U.S. Government purposes. Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy. Los Alamos National Laboratory strongly supports academic freedom and a researcher's right to publish; as an institution, however, the Laboratory does not endorse the viewpoint of a publication or guarantee its technical correctness.

TSA Radiation Portal Monitor SC-770 Telnet Connection Using Tera Term

Tera Term is open-source telnet communications software, available from <http://ttssh2.sourceforge.jp/index.html.en> and other websites. This software provides a simple way to connect a computer to the Ethernet output of the SC-770 in a TSA radiation portal monitor (RPM). Streaming the data output can be useful for monitoring the status of an RPM, performing diagnostics, and recordkeeping.

After downloading the software and copying the Tera Term folder to your computer [teraterm-4.xx], the next two steps are to

- configure your computer's Network and Sharing settings and
- configure the Tera Term connection settings.

To accomplish these steps, first

1. Connect your computer to the SC-770 via Ethernet.
2. Go to your computer's *Control Panel*>*Network and Sharing Center* (an "Unidentified network" should be showing).
3. Select the *Connections: Local Area Connection* link.

4. Select *Properties* in the *Local Area Connection Status* window.

5. Select *Internet Protocol Version 4 (TCP/IPv4)* from the list in the *Local Area Connection Properties* window, then

5.a. Select *Properties*.

6. In the *Internet Protocol Version 4 (TCP/IPv4) Properties* window, enter an IP address (for the computer) that is one or two numbers different from the IP address of the RPM.
(E.g., if the SC-770's IP address is 192.168.001.100,

enter 192.168.001.101 for your laptop.)

- 6.a. Select *OK* [*Internet Protocol Version 4 (TCP/IPv4) Properties* window].
- 6.b. Select *OK* (*Local Area Connection Properties* window).
- 6.c. Select *Close* (*Local Area Connection Status* window).
- 6.d. Close the *Network & Sharing Center* window (optional).

7. Start Tera Term. In the *New connection* window,

- 7.a. Select the *TCP/IP* radio button (default).
- 7.b. Enter the *IP address* of the RPM as the *Host*.
(Note: there must be three numbers in each field, e.g., 123.456.789.012.)
- 7.c. Select the *Telnet* radio button as the *Service*:
- 7.d. Enter *TCP port#* 1600.
- 7.e. Select *IPv4* from the *Protocol* menu.
- 7.f. Select *OK*.

Data should appear within a few seconds.